









Type	Profile				Description	Manual App Control	
	Fixture ID	Model / Name	Icon	Fixture mode			
DALI	41631**	DALI Lin* Broadcast		DALI/BC/Dim{OHI,H WTemp,Daylight}	DALI Broadcast. Linear dimming curve. Factory default profile. AUX output switches on when dimming level >0.	Dimmer: BC	Dimmer 100.0 %
	41632	DALI Lin* BC + iRelay		DALI/BC/Dim{OHI,H WTemp,Daylight}	DALI Broadcast. Linear dimming curve. Independent toggle switch control for the AUX output.	Dimmer: BC AUX: Open collector output	Dimmer 100.0 % AUX
	41633	DALI Log Broadcast		DALI/BC/Dim{OHI,H WTemp,Daylight}	DALI Broadcast. Logarithmic dimming curve. AUX output switches on when dimming level >0.	Dimmer: BC	Dimmer 100.0 %
	41634	DALI Lin* BC + Ext. Presence		DALI/BC/Dim{OHI,H WTemp,Presence,Daylight}	DALI Broadcast. Linear dimming curve. A DALI-2 motion sensor connected to the DALI bus will appear as a Casambi sensor in the App. AUX output switches on when dimming level >0.	Dimmer: BC	Dimmer 100.0 %
	41635	DALI Lin* BC + Ext. Sensors		DALI/BC/Dim{OHI,H WTemp,Presence,Daylight}	DALI Broadcast. Linear dimming curve. A DALI-2 motion and light sensor connected to the DALI bus will appear as a Casambi sensor in the App. AUX output switches on when dimming level >0.	Dimmer: BC	Dimmer 100.0 %
	41636	DALI Lin* 1xDIM SA		DALI/Elements{OHI,H WTemp,Daylight}	DALI DT6 1xDimmer. Linear dimming curve. Automatic DALI addressing. AUX output switches on when dimming level >0.	Dimmer: A0	A0 100.0 %
	41637	DALI Lin* 2xDIM SA		DALI/Elements{OHI,H WTemp,Daylight}	DALI DT6 2xDimmers. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing. AUX output switches on when dimming level >0.	Dimmer 1: A0 Dimmer 2: A1	A0 100.0 % A1 100.0 %
	41638	DALI Lin* 3xDIM SA		DALI/Elements{OHI,H WTemp,Daylight}	DALI DT6 3xDimmers. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing. AUX output switches on when dimming level >0.	Dimmer 1: A0 Dimmer 2: A1 Dimmer 3: A2	A0 100.0 % A1 100.0 % A2 100.0 %
	41639	DALI Lin* 4xDIM SA		DALI/Elements{OHI,H WTemp,Daylight}	DALI DT6 4xDimmers. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing. AUX output switches on when dimming level >0.	Dimmer 1: A0 Dimmer 2: A1 Dimmer 3: A2 Dimmer 4: A3	A0 100.0 % A1 100.0 % A2 100.0 % A3 100.0 %
41640	DALI Lin* 5xDIM SA		DALI/Elements{OHI,H WTemp,Daylight}	DALI DT6 5xDimmers. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing. AUX output switches on when dimming level >0.	Dimmer 1: A0 Dimmer 2: A1 Dimmer 3: A2 Dimmer 4: A3 Dimmer 5: A4	A0 100.0 % A1 100.0 % A2 100.0 % A3 100.0 % A4 100.0 %	



	41641	DALI Lin* 6xDIM SA		DALI/Elements{OHI,H WTemp,Daylight}	DALI DT6 6xDimmers. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing. AUX output switches on when dimming level >0.	Dimmer 1: A0 Dimmer 2: A1 Dimmer 3: A2 Dimmer 4: A3 Dimmer 5: A4 Dimmer 6: A5	
	41642	DALI Lin* 7xDIM SA		DALI/Elements{OHI,H WTemp,Daylight}	DALI DT6 7xDimmers. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing. AUX output switches on when dimming level >0.	Dimmer 1: A0 Dimmer 2: A1 Dimmer 3: A2 Dimmer 4: A3 Dimmer 5: A4 Dimmer 6: A5 Dimmer 7: A6	
	41644	DALI Lin* 8xDIM SA		DALI/Elements{OHI,H WTemp,Daylight}	DALI DT6 8xDimmers. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing. AUX output switches on when dimming level >0.	Dimmer 1: A0 Dimmer 2: A1 Dimmer 3: A2 Dimmer 4: A3 Dimmer 5: A4 Dimmer 6: A5 Dimmer 7: A6 Dimmer 8: A7	
	41645	DALI Lin* (1xGroup)		DALI/Elements{OHI,H WTemp,Daylight}	DALI 1xGroup. Linear dimming curve. Controls DALI groups. AUX output switches on when dimming level >0.	Dimmer: G0	
	41646	DALI Lin* (2xGroup)		DALI/Elements{OHI,H WTemp,Daylight}	DALI 2xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups. AUX output switches on when dimming level >0.	Dimmer 1: G0 Dimmer 2: G1	
	41647	DALI Lin* (3xGroup)		DALI/Elements{OHI,H WTemp,Daylight}	DALI 3xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups. AUX output switches on when dimming level >0.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2	
	41648	DALI Lin* (4xGroup)		DALI/Elements{OHI,H WTemp,Daylight}	DALI 4xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups. AUX output switches on when dimming level >0.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3	






	41649	DALI Lin* (5xGroup)		DALI/Elements{OHI,H WTemp,Daylight}	DALI 5xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups. AUX output switches on when dimming level >0.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3 Dimmer 5: G4	
	41650	DALI Lin* (6xGroup)		DALI/Elements{OHI,H WTemp,Daylight}	DALI 6xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups. AUX output switches on when dimming level >0.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3 Dimmer 5: G4 Dimmer 6: G5	
	41651	DALI Lin* (7xGroup)		DALI/Elements{OHI,H WTemp,Daylight}	DALI 7xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups. AUX output switches on when dimming level >0.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3 Dimmer 5: G4 Dimmer 6: G5 Dimmer 7: G6	
	41652	DALI Lin* (8xGroup)		DALI/Elements{OHI,H WTemp,Daylight}	DALI 8xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups. AUX output switches on when dimming level >0.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3 Dimmer 5: G4 Dimmer 6: G5 Dimmer 7: G6 Dimmer 8: G7	
	41653	DALI Lin* DT6 TW Warm-Cool SA		DALI/2ch/Dim,Vertic al{OHI,HWTemp,Dayl ight}	DALI DT6 Tunable white. Generic Warm / Cool slider (no CCT value data). Linear dimming curve. Automatic DALI addressing. AUX output switches on when dimming level >0. Warm: address A0 Cool: address A1	Dimmer: A0+A1 Warm/Cool: Colour temperature mixer	
	42327	DALI Lin* DT6 TW 3- 5K SA		DALI/2ch/Dim,TW{O HI,HWTemp,Daylight}	DALI DT6 Tunable white. Linear dimming curve. Automatic DALI addressing. AUX output switches on when dimming level >0. Warm: address A0 Cool: address A1	Dimmer: A0+A1 Colour temperature: Warm (3000K) / cool (5000k) mixer	



	41654	DALI Lin* DT6 RGB SA		DALI/3ch/Dim,RGB{OHI,HWTemp,Daylight}	DALI DT6 RGB. Linear dimming curve. Automatic DALI addressing. AUX output switches on when dimming level >0. Red: address A0 Green: address A1 Blue: address A2	Dimmer: Red/green/blue/ dimming control Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	
	41655	DALI Lin* DT6 RGB/W SA		DALI/4ch/Dim,RGB/White{OHI,HWTemp,Daylight}	DALI DT6 RGB/W. Linear dimming curve. White/Colour balance control. Automatic DALI addressing. AUX output switches on when dimming level >0. Red: address A0 Green: address A1 Blue: address A2 White: address A3	Dimmer: Red/green/blue/white dimming control White/Colour: Balance between the white channel and the RGB mix Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color (doesn't affect the white channel) Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	
	41656	DALI Lin* DT6 RGB/W+IW SA		DALI/5ch/Dim,RGB/W+W[Evolution]{OHI,HWTemp,Daylight}	DALI DT6 RGB/W with additional White channel. Linear dimming curve. White/Colour balance slider + Dedicated slider for additional White channel independent from main dimmer. Automatic DALI addressing. AUX output switches on when dimming level >0. Red: address A0 Green: address A1 Blue: address A2 White (White/Colour slider): address A3 White (independent slider): address A4	Dimmer: Red/green/blue/white (A3) dimming control White: Independent White channel dimming control (A4) White/Colour: Balance between the white channel (A3) and the RGB mix Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color (doesn't affect the white channels) Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	
DALI DT8	41657	DALI Lin* DT8 Dim to Warm BC		DALI/DT8/Dim[Warm Cool]{OHI,HWTemp}	DALI DT8 Dim to Warm. Broadcast. Single dimmer controlling both light intensity and color temperature. Light is warmer at low dimming levels and cooler at higher brightness levels. Linear dimming curve. AUX output switches on when dimming level >0.	Dimmer: BC	
	41658	DALI Lin* DT8 TW 1.8-3K BC		DALI/DT8/Dim,TW{OHI,HWTemp,Daylight}	DALI DT8 Tunable white. Broadcast. Linear dimming curve. AUX output switches on when dimming level >0.	Dimmer: BC Colour temperature: Warm (1800K) / cool (3000K) mixer	
	41659	DALI Lin* DT8 TW 3-5K BC		DALI/DT8/Dim,TW{OHI,HWTemp,Daylight}	DALI DT8 Tunable white. Broadcast. Linear dimming curve. AUX output switches on when dimming level >0.	Dimmer: BC Colour temperature: Warm (3000K) / cool (5000K) mixer	
	41660	DALI Lin* DT8 TW 1-10K BC		DALI/DT8/Dim,TW{OHI,HWTemp,Daylight}	DALI DT8 Tunable white. Broadcast. Linear dimming curve. AUX output switches on when dimming level >0.	Dimmer: BC Colour temperature: Warm (1000K) / cool (10000K) mixer	



	41661	DALI Lin* DT8 RGB BC		DALI/DT8/Dim,RGB{OHI,HWTmp,Daylight}	DALI DT8 RGB. Broadcast. Linear dimming curve. AUX output switches on when dimming level >0.	Dimmer: Red/green/blue dimming control Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	
	41662	DALI Lin* DT8 RGB/W BC		DALI/DT8/Dim,RGB/White [Evolution] {OHI,HWTmp,Daylight}	DALI DT8 RGB/W. Broadcast. Linear dimming curve. White/Colour balance slider. AUX output switches on when dimming level >0.	Dimmer: Red/green/blue/white dimming control White/Colour: Balance between the white channel and the RGB mix Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color (doesn't affect the white channel) Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	
	41663	DALI Lin* DT8 XY BC		DALI/DT8/Dim,XY [Evolution] {OHI,HWTmp,Daylight}	DALI DT8 XY. Broadcast. Linear dimming curve. AUX output switches on when dimming level >0.	Dimmer: BC X: Colour based on "x" coordinate Y: Colour based on "y" coordinate XY Palette: Red/green/blue mix based on "x, y" coordinates	
Misc.	41664	Light Sensor		Sensor{OHI,HWTmp,Daylight}	Light Sensor fixture profile. It doesn't appear under Lamps tab.	-	It appears under the "Sensors" Tab.

** Default profile

Additional information

Summary of some terms and abbreviations that have been used throughout the document.

Abbreviation:	Description:
A0, A1, A2, ...	DALI short address.
G0, G1, G2, ...	DALI group address.
BC	Broadcast.
SA	Short Address.
Lin*	Optimized linear dimming curve.
Log	Logarithmic dimming curve.
AUX	Open collector output referenced to DA(0V)



Revision history

Date:	Version:	Description:
07/05/2024	1.0	Initial release.
15/04/2025	1.1	New fixture profiles for V2 hardware.