
















Type	Profile				Description	Manual App Control	
	Fixture ID	Model / Name	Icon	Fixture mode			
DALI	43334	DALI Lin* Broadcast		DALI/BC/Dim{Presence,Daylight}	Presence and light sensor. DALI Broadcast. Linear dimming curve.	Dimmer: BC	
	43335	DALI Log Broadcast		DALI/BC/Dim{Presence,Daylight}	Presence and light sensor. DALI Broadcast. Logarithmic dimming curve.	Dimmer: BC	
	43337	DALI Lin* BC + Ext. Buttons		DALI/BC/Dim{Presence,DALIPB,Daylight}	Presence and light sensor. DALI Broadcast. Linear dimming curve. A DALI-2 Push button input device with up to 8 instances (iN0 - iN7) connected to the DALI bus will appear as the same number of Cosambi push buttons in the App.	Dimmer: BC	
	43338	DALI Log BC + Ext. Buttons		DALI/BC/Dim{Presence,DALIPB,Daylight}	Presence and light sensor. DALI Broadcast. Logarithmic dimming curve. A DALI-2 Push button input device with up to 8 instances (iN0 - iN7) connected to the DALI bus will appear as the same number of Cosambi push buttons in the App.	Dimmer: BC	
	43339	DALI Lin* 1xDIM SA		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI DT6 1xDimmer. Linear dimming curve. Automatic DALI addressing.	Dimmer: A0	
	43340	DALI Log 1xDIM SA		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI DT6 1xDimmer. Logarithmic dimming curve. Automatic DALI addressing.	Dimmer: A0	
	43341	DALI Lin* 2xDIM SA		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI DT6 2xDimmers. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing.	Dimmer 1: A0 Dimmer 2: A1	
	43342	DALI Log 2xDIM SA		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI DT6 2xDimmers. Logarithmic dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing.	Dimmer 1: A0 Dimmer 2: A1	
	43343	DALI Lin* 4xDIM SA		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI DT6 4xDimmers. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing.	Dimmer 1: A0 Dimmer 2: A1 Dimmer 3: A2 Dimmer 4: A3	
	43344	DALI Log 4xDIM SA		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI DT6 4xDimmers. Logarithmic dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing.	Dimmer 1: A0 Dimmer 2: A1 Dimmer 3: A2 Dimmer 4: A3	
	43345	DALI Lin* 8xDIM SA		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI DT6 8xDimmers. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing.	Dimmer 1: A0 Dimmer 2: A1 Dimmer 3: A2 Dimmer 4: A3 Dimmer 5: A4 Dimmer 6: A5 Dimmer 7: A6 Dimmer 8: A7	










	43346	DALI Log 8xDIM SA		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI DT6 8xDimmers. Logarithmic dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Automatic DALI addressing.	Dimmer 1: A0 Dimmer 2: A1 Dimmer 3: A2 Dimmer 4: A3 Dimmer 5: A4 Dimmer 6: A5 Dimmer 7: A6 Dimmer 8: A7	
	43347	DALI Lin* (1xGroup)		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI 1xGroup. Linear dimming curve. Controls DALI groups.	Dimmer: G0	
	43348	DALI Log (1xGroup)		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI 1xGroup. Logarithmic dimming curve. Controls DALI groups.	Dimmer: G0	
	43349	DALI Lin* (2xGroup)		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI 2xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups.	Dimmer 1: G0 Dimmer 2: G1	
	43350	DALI Log (2xGroup)		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI 2xGroup. Logarithmic dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups.	Dimmer 1: G0 Dimmer 2: G1	
	43351	DALI Lin* (4xGroup)		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI 4xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3	
	43352	DALI Log (4xGroup)		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI 4xGroup. Logarithmic dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3	
	43353	DALI Lin* (8xGroup)		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI 8xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3 Dimmer 5: G4 Dimmer 6: G5 Dimmer 7: G6 Dimmer 8: G7	





	43354	DALI Log (8xGroup)		DALI/Elements{Presence,Daylight}	Presence and light sensor. DALI 8xGroup. Logarithmic dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3 Dimmer 5: G4 Dimmer 6: G5 Dimmer 7: G6 Dimmer 8: G7	
	43355	DALI Lin* (8xGroup) + Ext. Buttons		DALI/Elements{Presence,DALIPB,Daylight}	Presence and light sensor. DALI 8xGroup. Linear dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups. A DALI-2 Push button input device with up to 8 instances (iN0 - iN7) connected to the DALI bus will appear as the same number of Casambi push buttons in the App.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3 Dimmer 5: G4 Dimmer 6: G5 Dimmer 7: G6 Dimmer 8: G7	
	43356	DALI Log (8xGroup) + Ext. Buttons		DALI/Elements{Presence,DALIPB,Daylight}	Presence and light sensor. DALI 8xGroup. Logarithmic dimming curve. Individual slider levels are overwritten when dimmed by sliding on the App icon. Controls DALI groups. A DALI-2 Push button input device with up to 8 instances (iN0 - iN7) connected to the DALI bus will appear as the same number of Casambi push buttons in the App.	Dimmer 1: G0 Dimmer 2: G1 Dimmer 3: G2 Dimmer 4: G3 Dimmer 5: G4 Dimmer 6: G5 Dimmer 7: G6 Dimmer 8: G7	
	43357	DALI Lin* DT6 TW Warm-Cool SA		DALI/2ch/Dim,Vertical{Presence,Daylight}	Presence and light sensor. DALI DT6 Tunable white. Generic Warm / Cool slider (no CCT value data). Linear dimming curve. Automatic DALI addressing. Warm: address A0 Cool: address A1	Dimmer: A0+A1 Warm/Cool: Colour temperature mixer	
	43358	DALI Log DT6 TW Warm-Cool SA		DALI/2ch/Dim,Vertical{Presence,Daylight}	Presence and light sensor. DALI DT6 Tunable white. Generic Warm / Cool slider (no CCT value data). Logarithmic dimming curve. Automatic DALI addressing. Warm: address A0 Cool: address A1	Dimmer: A0+A1 Warm/Cool: Colour temperature mixer	
	43359	DALI Lin* DT6 Dim to Warm SA		DALI/2ch/Dim{Warm Cool}{Presence,Daylight}	Presence and light sensor. DALI DT6 Dim to Warm. Single dimmer controlling both light intensity and color temperature. Light is warmer at low dimming levels and cooler at higher brightness levels. Linear dimming curve. Automatic DALI addressing. Warm: address A0 Cool: address A1	Dimmer: A0+A1	
	43360	DALI Log DT6 Dim to Warm SA		DALI/2ch/Dim{Warm Cool}{Presence,Daylight}	Presence and light sensor. DALI DT6 Dim to Warm. Single dimmer controlling both light intensity and color temperature. Light is warmer at low dimming levels and cooler at higher brightness levels. Logarithmic dimming curve. Automatic DALI addressing. Warm: address A0 Cool: address A1	Dimmer: A0+A1	



	43361	DALI Lin* DT6 RGB/W SA		DALI/4ch/Dim,RGB/White{Presence,Daylight}	Presence and light sensor. DALI DT6 RGB/W. Linear dimming curve. White/Colour balance control. Automatic DALI addressing. Red: address A0 Green: address A1 Blue: address A2 White: address A3	Dimmer: Red/green/blue/white dimming control White/Colour: Balance between the white channel and the RGB mix Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color (doesn't affect the white channel) Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	
	43362	DALI Log DT6 RGB/W SA		DALI/4ch/Dim,RGB/White{Presence,Daylight}	Presence and light sensor. DALI DT6 RGB/W. Logarithmic dimming curve. White/Colour balance control. Automatic DALI addressing. Red: address A0 Green: address A1 Blue: address A2 White: address A3	Dimmer: Red/green/blue/white dimming control White/Colour: Balance between the white channel and the RGB mix Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color (doesn't affect the white channel) Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	
DALI DT8	43363	DALI Lin* DT8 TW 2.7-6.5K BC		DALI/DT8/Dim,TW{Presence,Daylight}	Presence and light sensor. DALI DT8 Tunable white. Broadcast. Linear dimming curve.	Dimmer: BC Colour temperature: Warm (2700K) / cool (6500K) mixer	
	43364	DALI Log DT8 TW 2.7-6.5K BC		DALI/DT8/Dim,TW{Presence,Daylight}	Presence and light sensor. DALI DT8 Tunable white. Broadcast. Logarithmic dimming curve.	Dimmer: BC Colour temperature: Warm (2700K) / cool (6500K) mixer	
	43365	DALI Lin* DT8 Dim to Warm BC		DALI/DT8/Dim,[Warm Cool]{Presence,Daylight}	Presence and light sensor. DALI DT8 Dim to Warm. Broadcast. Single dimmer controlling both light intensity and color temperature. Light is warmer at low dimming levels and cooler at higher brightness levels. Linear dimming curve.	Dimmer: BC	
	43366	DALI Log DT8 Dim to Warm BC		DALI/DT8/Dim,[Warm Cool]{Presence,Daylight}	Presence and light sensor. DALI DT8 Dim to Warm. Broadcast. Single dimmer controlling both light intensity and color temperature. Light is warmer at low dimming levels and cooler at higher brightness levels. Logarithmic dimming curve.	Dimmer: BC	
	43367	DALI Lin* DT8 RGB/W BC		DALI/DT8/Dim,RGB/White{Evolution}{Presence,Daylight}	Presence and light sensor. DALI DT8 RGB/W. Broadcast. Linear dimming curve. White/Colour balance slider.	Dimmer: Red/green/blue/white dimming control White/Colour: Balance between the white channel and the RGB mix Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color (doesn't affect the white channel) Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	
	43368	DALI Log DT8 RGB/W BC		DALI/DT8/Dim,RGB/White{Evolution}{Presence,Daylight}	Presence and light sensor. DALI DT8 RGB/W. Broadcast. Logarithmic dimming curve. White/Colour balance slider.	Dimmer: Red/green/blue/white dimming control White/Colour: Balance between the white channel and the RGB mix Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color (doesn't affect the white channel) Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	



	43369	DALI Lin* DT8 RGB/TW BC		DALI/DT8/Dim,RGB,TW{Presence,Daylight}	Presence and light sensor. DALI DT8 RGB/TC. Broadcast. Linear dimming curve.	Dimmer: Red/green/blue/warm/cool dimming control Colour temperature: Warm (2700K) / cool (6500K) mixer Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color (doesn't affect warm or cool channel) Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	
	43370	DALI Log DT8 RGB/TW BC		DALI/DT8/Dim,RGB,TW{Presence,Daylight}	Presence and light sensor. DALI DT8 RGB/TC. Broadcast. Logarithmic dimming curve.	Dimmer: Red/green/blue/warm/cool dimming control Colour temperature: Warm (2700K) / cool (6500K) mixer Colour: Red/green/blue mixer Colour saturation: Grade of purity of the current color (doesn't affect warm or cool channel) Palette: Red/green/blue mix (horizontal) + saturation (vertical) Saved colours: Up to 10	
Misc.	43371**	Sensor + Push Button		Sensor{Presence,Daylight}	Sensor and Push button fixture. Presence and light sensor. It doesn't appear under Lamps tab. A single normally open (N.O.) push button should be wired to the DALI (DA+/DA-) terminals. Factory default profile.	-	It appears under "Sensors" and "Switches" tab. PUSH BUTTONS DALI Not Used Select the device's button functions

** Default profile.

All fixture profiles include a Casambi parameter that allows disabling the internal presence indicator LED.

Additional information

Summary of some terms and abbreviations that have been used throughout the document.

Abbreviation:	Description:
A0, A1, A2, ...	DALI short address.
G0, G1, G2, ...	DALI group address.
BC	Broadcast.
SA	Short Address.
Lin*	Optimized linear dimming curve.
Log	Logarithmic dimming curve.



Revision history

Date:	Version:	Description:
25/10/2025	1.0	Initial release.