

# SC-TI-CAS Casambi-Tasterinterface

CASAMBI

Art.-Nr.: 0516.001.550

## EASY TO SET UP

The interface is automatically recognized by the Casambi app and can be integrated into the existing network, just one click is enough.

## FUNCTIONAL DIVERSITY

Each button can be individually configured via the Casambi app. As a scene button, to call up animations or to dimming or switching a particular light or luminaire group.

## SIMPLE INTEGRATION

The interface fits into any flush-mounted socket. Depending on the pushbutton used, a deep flush-mounting box is recommended.

For further information about all our products visit our website:

[www.scemtec-gmbh.de](http://www.scemtec-gmbh.de)

Or contact us at:

[www.olfer.com](http://www.olfer.com)



The SC-TI-CAS is an input module for up to 4 potential-free buttons. The device is automatically recognized by the Casambi app and can be included in the existing network. The functions triggered by the buttons can be configured with the Casambi app.

The interface is supplied with mains voltage and can be installed in a flush-mounted socket. If a push-button is additionally installed in the flush-mounted box, a deep flush-mounted box is recommended. A 4-way button insert, e.g. GIRA 014 700, could be used or a combination of single and / or double pushbuttons in several flush-mounted boxes.

## Technical specifications

Power supply	230VAC, 50Hz
Power consumption	max. 10mA
Cable length of button connections	max. 30cm
Ambient temperature	0 - 55°C
Applied standards	DIN EN 60669-2-1 ETSI EN 301 489-1 v.1.9.2 ETSI EN 301 489-17 v.2.2.1 ETSI EN 300 328 v.1.8.1  <b>NOTE!</b> The connected pushbuttons and their wiring must be insulated for the maximum supply voltage of the push button interface and ensure the appropriate contact protection after proper installation.
Dimensions	Ø 53mm x 21mm