



ZHAGA



■ Characteristics

- Female Zhaga socket for luminaries
- Easy to install
- Zhaga Certified

■ Applications

- Street light luminaries
- Outdoor lighting applications
- Decorative lighting

■ Description

The OLF-041 is a two parts screw socket to mount on luminaries to prepare them for Zhaga. It is delivered in 2 parts for easy assembly. Just drill a 20mm hole on the luminary and insert both parts using the silicone integrated sealing gasket for watertight protection

■ Main Features

- Zhaga Book 18 standard
- Rated voltage 30Vdc/ac
- Rated load 1.5 Amps (max)
- Body material PBT
- Silicone sealing gasket
- Easy installation

■ Specifications

Model	OLF-041	
Input / Output	Rated voltage	30Vdc/ac (max)
	Rated current	1.5 Amps (max)
Standard	Zhaga book 18	
Materials	Body receptable	PBT
	Sealing gasket	Silicone
Connections	Pin 1	Positive (+) pole (24V from power supply)
	Pin 2	Negative (-) pole for DALI protocol Negative (-) pole for 24V power supply Ground for general Digital I/O contacts
	Pin 3	Positive (+) pole for DALI protocol
	Pin 4	General digital I/O (greater than 7V)
Others	Dimensions	Diameter 38 mm. Height 26.5 mm
	Weight	35gr
	Box (2 units per box)	10 x 6,5 x 4cm / 0,076Kg
	Packing	200 Units per box. 52 x 29 x 23cm / 8,15kg
	Color	Black

■ Dimensions

